

APPROVED DOC 'P' (Notifiable)

List of works that is notifiable to local authority and/or must be completed by a company registered as a “competent person”.

	Extensions and modifications to circuits	New Circuits
Bathrooms	✓	✓
Bedrooms	x	✓
Bedrooms containing a shower or basin	✓	✓
Ceiling (over head) heating	✓	✓
Communal area of flats	✓	✓
Computer cabling	x	x
Conservatories	x	✓
Dining rooms	x	✓
Down Lighters (E.L.V.) non pre-assembled CE marked lights	✓	✓
Garden – lighting	✓	✓
Gardens – power	✓	✓
Greenhouses	✓	✓
Halls	x	✓
Integral garages	x	✓
Kitchen	✓	✓
Kitchen Diners	✓	✓

	Extensions and modifications to circuits	New Circuits
Landings	x	✓
Lounge	x	✓
Remote buildings	✓	✓
Remote garages	✓	✓
Saunas	✓	✓
Sheds	✓	✓
Shower rooms	✓	✓
Small scale generators	✓	✓
Solar power systems	✓	✓
Stairways	x	✓
Studies	x	✓
Swimming pools	✓	✓
Telephone cabling	x	x
TV rooms	x	✓
Under floor heating	✓	✓
Workshops (remote)	✓	✓

*** Kitchen is defined as ‘a room or part of a room which contains a sink and food preparation facilities’. In open plan areas the zone of a kitchen may be considered to extend from the edge of the sink to a distance of 3 metres or to a nearer dividing wall**